

Sennheiser Control Cockpit: EW-DX control, monitoring and firmware updates

To control, monitor and perform firmware updates for EW-DX you will need our Sennheiser Control Cockpit software. This document outlines how to install and configure Control Cockpit and update your EW-DX products.

Installing Control Cockpit

The installation file of the Sennheiser Control Cockpit software can be downloaded from the Sennheiser Control Cockpit product page: <u>Control Cockpit audio software | Sennheiser</u>

Follow these simple steps to have the software installed:

- Save the downloaded installation file SennheiserControlCockpitInstaller.exe on the host PC
- Start the installation process
- Agree to the license terms and conditions
- Click Next

		-
Cense Agreement		
Please read the following important information before continuing.		SEN
Please read the following License Agreement. You must accept the terms of this agreement be continuing with the installation.	efore	
		^
Sennheiser Control Cockpit Application		
Copyright (c) 2016-2022, Sennheiser electronic GmbH & Co. KG	3	
LICENSE AGREEMENT "Sennheiser Control Cockpit Application VERSION (ANY)	on"	
LICENSE AGREEMENT		
		~
I accept the agreement		
○ I do not accept the agreement		

• Adjust the settings as desired and click Next



Setup - Sennheiser Control Cockpit version 6.0.0	82		×
Setup Options			SENNHEISEN
Server Port:			_
Proxy Url:			
Proxy Port:			
Back	<u>N</u> ext	Ca	ancel

- Please remember to include https:// for the proxy URL (if used).
- If you want to use Sennheiser Control Cockpit in parallel with Sennheiser Wireless Systems Manager or any other application on the same machine already using port 8181, please type in another port (e.g. 8080 or 8282).
- Choose whether you want to create a desktop shortcut and click Next.



SENNHEISER



• Click Install to start the installation process.



• The Sennheiser Control Cockpit is now installed. Afterwards, the following dialog is displayed.



- Click Finish to complete the installation.
- Before using Control Cockpit for the first time you need to enter your Activation Key





 Click on **Get your activation key** to open the following address: <u>www.sennheiser.com/control-</u> <u>cockpit-registration</u>

100 A	STATE OF THE OWNER OF THE OWNER OF	
	Welcome to the	tion water
	Sennheiser Control Co	ckpit
51		
	Tool Registration	50
	Please register with Sennheiser to use the Sennheise registration is completely free.	r Control Cockpit. The na tensing lettery 16 an 3 LAB
	Get your activation key <u>Need help?</u>	هه و در مع مدانه و معن
		b Linna Agentent 🕤 Linn Armed
	Please enter the User ID and the Activation Key, which registration.	h you received after your
	User ID user@example.com	
	Activation Key XXX-XXXX-XXXXX-X	
		Activate

Click on Activate after you have received your activation key

For further instructions on how to use Sennheiser Control Cockpit, please refer to the following manual: <u>Sennheiser Control Cockpit – Software Manual</u>



Updating EW-DX

Once Sennheiser Control Cockpit software is installed and activated, you can proceed to updating EW-DX devices.

Please follow these simple steps:

• Connect EW-DX to the same network as your PC

Device List 0/	2 devices					+ Add device	🗗 Export list
Search		Filter by type	Filter by location	Filter by device state	Filter by battery life	Filter on identify	Show all
Type Name		Device Information		Transmitter Type	Battery Re	maining :	Identify
	KEM2						Ø
<mark>■ <u>User Manual</u> ⊀</mark> © 2016-2022 by Seni Are you missing a fe	★ Settings ▲ Privacy ① II nheiser electronic GmbH & Co. ature? <u>Tell us about your idea!</u>	n <u>fo</u> KG Version 6.0.0					⊕ EN ∨

- EW-DX will be automatically discovered by Control Cockpit
- In case your EW-DX device is not populating automatically in the Device List, please use the link "Add device" to add the device manually using the device's IP address
- Go to the device page and select the latest available firmware (**firmware 1.1.3** as of November 2022), accept the license agreement, and update your receiver

Devices selected # Monitoring View								onitoring View		
Туре	Name			vice Information		Transmitter Type	Battery		uality Pairi	ng Identify
ii ii ii	EWDXEM2		1							Ø
1	EW-DX 1		/							Ø
2	EW-DX 2		/							0
Prop	erties									
-	Audio	Device	👬 Network	۳) RF Settings						
EW-D	X EM 2 1 sele									•
Firm	ware Info	0	Name	0	Location	0	Display Brightness	(i)	Serial Number	(j)
Firmware 1.1.3		EWDXEM2				Please update device firmware this setting	ise update device firmware to use 53020 this setting			
1.1.3 - via update server										
		Device Restart	0	Factory Reset	0					
		I Restarts your dev audio link will be	OK I nice. An active Interrupted.	II I Click to enable	OK I reset					
User Manual & Settings A Privacy O Info						∰ EN ~				
© 2016-2022 by Sennheiser electronic GmbH & Co. KG Version 6.0.0 Are you missing a feature? <u>Tell us about your idea!</u>										

• Your EW-DX has been successfully updated

For conformity, consistency and compatibility reasons, we strongly recommend always upgrading the system to the new release.

SENNHEISER